






Residential ESS

LiFePO4 Lithium Battery Pack Portable Model



Product Features:


- 
Higher Safe Performance and Longer Cycle Life
 With breaker and fuse
- 
High Scalability
 Up to 15pcs to connect in parallel
- 
Wide Compatibility
 Compatible with most of the leading inverter brands
- 
Advanced Battery Management System
 Smart BMS from famous brands, to monitor the battery's temperature, current, prevent over-current and etc. Take good control of the charging and discharging of battery to max. the lifespan
- 
Environmentally Friendly
 From reduced carbon emissions to increased energy savings, we've got you covered. It will help reduce your carbon footprint by storing energy from renewable sources like solar power and wind power

Model	PNG-E48280-LV	PNG-E51280-LV
Nominal Voltage	48V	51.2V
Nominal Capacity	280Ah	
Nominal Energy	13.44kWh	14.34kWh
Output Voltage Range	40.5-54.75V	43.2-58.4V
Charge Voltage Range	48-54.75V	51.2-58.4V
Discharge Cut-off Voltage	40.5V	43.2V
Max. Charge/ Discharge Current	200A	
Recommend Charge Current (Continuous)	70A	
Scalability	Up to 15pcs connected in parallel	
Depth of Discharge (DOD)	90%/25°C/0.5C, SOC ≥ 80%	
Display Type	LCD Screen	
Protection Level	IP54(Indoor)	
Working Temperature Range	Charge: 0°C~+55°C. Discharge: -20°C~+55	
Storage Temperature Range	-10°C~+30°C	
Humidity	5%~95% RH	
Cycle Life	≥800cycles	
Protection	Built-in smart BMS, Breaker, Fuse	
Communication Port	CAN / RS485	
Warranty	5years	
Installation	Wall-Mounted	
Cooling Mode	Air-cooling	
Dimension(L*W*H)	550*270*728mm	
Weight	114kgs	120kgs

Application Scenarios



Refrigerator



Air System



Lighting



Small Home Appliances

1. Charging Management

- a. Pls use the lithium battery charger.
- b. It's forbidden to charge the battery under 0°C.

2. Discharging Management

- a. Pls charge the battery in time after the battery discharging cut-off to protect the battery cells.
- b. Please avoid consistent discharging with high-current (>1C), in case of over-heat.

3. Cautions

- a. It's forbidden to disassemble, puncture or crash the battery.
- b. It's forbidden to immerse the battery into the water or expose to the fire.
- c. It's forbidden to mix using the old and new batteries or different brands of batteries.

